

## micro BAND DECODER + WX0B SixPack™

The WX0B SixPack™ may be used with two micro Band Decoders forming a system for automatic switching of antennas for SO2R. Connect each micro Band Decoder according to the following table:

<b>BAND DATA OUTPUT connector pin number:</b>	<b>WX0B SixPack™ terminal number:</b>	<b>Antenna Port</b>
20	1	1
21	2	2
22	3	3
23	4	4
24	5	5
25	6	6
18	RET	

Using the supplied configuration software, choose the appropriate antenna port for each band. Use one antenna port for more than one band (multi band antennas), or multiple ports for a single band (frequency split), as necessary. Both decoders must be configured in the same way.

If the Six Pack is going to be placed outside, the optional RELAY BOARD must be installed. In this case, the jumper on the RELAY BOARD must be set to "+".